

| MODBUS REGISTER TABLOSU | | | | | | |
|-------------------------|---------------|-------------------|-----|-------|-------------------|--|
| ADDRESS | ADDRESS (HEX) | REGISTER | R/W | RANGE | FORMAT | |
| 0 | 0 | IN1 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 1 | 1 | | | | | |
| 2 | 2 | | | | | |
| 3 | 3 | | | | | |
| 4 | 4 | IN2 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 5 | 5 | | | | | |
| 6 | 6 | | | | | |
| 7 | 7 | | | | | |
| 8 | 8 | IN3 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 9 | 9 | | | | | |
| 10 | A | | | | | |
| 11 | B | | | | | |
| 12 | C | IN4 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 13 | D | | | | | |
| 14 | E | | | | | |
| 15 | F | | | | | |
| 16 | 10 | IN5 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 17 | 11 | | | | | |
| 18 | 12 | | | | | |
| 19 | 13 | | | | | |
| 20 | 14 | IN6 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 21 | 15 | | | | | |
| 22 | 16 | | | | | |
| 23 | 17 | | | | | |
| 24 | 18 | IN7 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 25 | 19 | | | | | |
| 26 | 1A | | | | | |
| 27 | 1B | | | | | |
| 28 | 1C | IN8 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 29 | 1D | | | | | |
| 30 | 1E | | | | | |
| 31 | 1F | | | | | |
| 32 | 20 | IN9 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 33 | 21 | | | | | |
| 34 | 22 | | | | | |
| 35 | 23 | | | | | |
| 36 | 24 | IN10 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 37 | 25 | | | | | |
| 38 | 26 | | | | | |
| 39 | 27 | | | | | |
| 40 | 28 | IN11 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 41 | 29 | | | | | |
| 42 | 2A | | | | | |
| 43 | 2B | | | | | |
| 44 | 2C | IN12 TOPLAM SAYAÇ | R/W | 0 | unsigned long int | |
| 45 | 2D | | | | | |
| 46 | 2E | | | | | |
| 47 | 2F | | | | | |

TOPLAM SAYAÇ ENDEKSLERİ

| | | | | | | |
|----|----|------------------------|-----|-----------|--------------|--|
| 48 | 30 | IN1 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 49 | 31 | IN1 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 50 | 32 | IN2 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 51 | 33 | IN2 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 52 | 34 | IN3 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 53 | 35 | IN3 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 54 | 36 | IN4 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 55 | 37 | IN4 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 56 | 38 | IN5 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 57 | 39 | IN5 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 58 | 3A | IN6 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 59 | 3B | IN6 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 60 | 3C | IN7 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 61 | 3D | IN7 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 62 | 3E | IN8 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 63 | 3F | IN8 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 64 | 40 | IN9 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 65 | 41 | IN9 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 66 | 42 | IN10 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 67 | 43 | IN10 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 68 | 44 | IN11 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 69 | 45 | IN11 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 70 | 46 | IN12 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 71 | 47 | IN12 T1 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 72 | 48 | IN1 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 73 | 49 | IN1 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |

TARİFELİ SAYAÇ ENDEKSLERİ

| MODBUS REGISTER TABLOSU | | | | | | |
|-------------------------|---------------|------------------------|-----|-----------|--------------|--|
| ADDRESS | ADDRESS (HEX) | REGISTER | R/W | RANGE | FORMAT | |
| 74 | 4A | IN2 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 75 | 4B | | | 0 - 65535 | unsigned int | |
| 76 | 4C | | | 0 - 65535 | unsigned int | |
| 77 | 4D | IN3 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 78 | 4E | | | 0 - 65535 | unsigned int | |
| 79 | 4F | | | 0 - 65535 | unsigned int | |
| 80 | 50 | IN4 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 81 | 51 | | | 0 - 65535 | unsigned int | |
| 82 | 52 | | | 0 - 65535 | unsigned int | |
| 83 | 53 | IN5 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 84 | 54 | | | 0 - 65535 | unsigned int | |
| 85 | 55 | | | 0 - 65535 | unsigned int | |
| 86 | 56 | IN6 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 87 | 57 | | | 0 - 65535 | unsigned int | |
| 88 | 58 | | | 0 - 65535 | unsigned int | |
| 89 | 59 | IN7 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 90 | 5A | | | 0 - 65535 | unsigned int | |
| 91 | 5B | | | 0 - 65535 | unsigned int | |
| 92 | 5C | IN8 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 93 | 5D | | | 0 - 65535 | unsigned int | |
| 94 | 5E | | | 0 - 65535 | unsigned int | |
| 95 | 5F | IN9 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 96 | 60 | | | 0 - 65535 | unsigned int | |
| 97 | 61 | | | 0 - 65535 | unsigned int | |
| 98 | 62 | IN10 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 99 | 63 | | | 0 - 65535 | unsigned int | |
| 100 | 64 | | | 0 - 65535 | unsigned int | |
| 101 | 65 | IN11 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 102 | 66 | | | 0 - 65535 | unsigned int | |
| 103 | 67 | | | 0 - 65535 | unsigned int | |
| 104 | 68 | IN12 T2 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 105 | 69 | | | 0 - 65535 | unsigned int | |
| 106 | 6A | | | 0 - 65535 | unsigned int | |
| 107 | 6B | IN1 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 108 | 6C | | | 0 - 65535 | unsigned int | |
| 109 | 6D | | | 0 - 65535 | unsigned int | |
| 110 | 6E | IN2 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 111 | 6F | | | 0 - 65535 | unsigned int | |
| 112 | 70 | | | 0 - 65535 | unsigned int | |
| 113 | 71 | IN3 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 114 | 72 | | | 0 - 65535 | unsigned int | |
| 115 | 73 | | | 0 - 65535 | unsigned int | |
| 116 | 74 | IN4 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 117 | 75 | | | 0 - 65535 | unsigned int | |
| 118 | 76 | | | 0 - 65535 | unsigned int | |
| 119 | 77 | IN5 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 120 | 78 | | | 0 - 65535 | unsigned int | |
| 121 | 79 | | | 0 - 65535 | unsigned int | |
| 122 | 7A | IN6 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 123 | 7B | | | 0 - 65535 | unsigned int | |
| 124 | 7C | | | 0 - 65535 | unsigned int | |
| 125 | 7D | IN7 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 126 | 7E | | | 0 - 65535 | unsigned int | |
| 127 | 7F | | | 0 - 65535 | unsigned int | |
| 128 | 80 | IN8 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 129 | 81 | | | 0 - 65535 | unsigned int | |
| 130 | 82 | | | 0 - 65535 | unsigned int | |
| 131 | 83 | IN9 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 132 | 84 | | | 0 - 65535 | unsigned int | |
| 133 | 85 | | | 0 - 65535 | unsigned int | |
| 134 | 86 | IN10 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 135 | 87 | | | 0 - 65535 | unsigned int | |
| 136 | 88 | | | 0 - 65535 | unsigned int | |
| 137 | 89 | IN11 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 138 | 8A | | | 0 - 65535 | unsigned int | |
| 139 | 8B | | | 0 - 65535 | unsigned int | |
| 140 | 8C | IN12 T3 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 141 | 8D | | | 0 - 65535 | unsigned int | |
| 142 | 8E | | | 0 - 65535 | unsigned int | |
| 143 | 8F | IN1 T4 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 144 | 90 | | | 0 - 65535 | unsigned int | |
| 145 | 91 | | | 0 - 65535 | unsigned int | |
| 146 | 92 | IN2 T4 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 147 | 93 | | | 0 - 65535 | unsigned int | |
| 148 | 94 | | | 0 - 65535 | unsigned int | |
| 149 | 95 | IN3 T4 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| | | | | 0 - 65535 | unsigned int | |
| | | | | 0 - 65535 | unsigned int | |

TARİFELİ SAYAÇ ENDEKSLERİ

| MODBUS REGISTER TABLOSU | | | | | | |
|-------------------------|---------------|------------------------|-----|-----------|--------------|--|
| ADDRESS | ADDRESS (HEX) | REGISTER | R/W | RANGE | FORMAT | |
| 150 | 96 | IN4 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 151 | 97 | | | 0 - 65535 | unsigned int | |
| 152 | 98 | | | 0 - 65535 | unsigned int | |
| 153 | 99 | IN5 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 154 | 9A | | | 0 - 65535 | unsigned int | |
| 155 | 9B | | | 0 - 65535 | unsigned int | |
| 156 | 9C | IN6 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 157 | 9D | | | 0 - 65535 | unsigned int | |
| 158 | 9E | | | 0 - 65535 | unsigned int | |
| 159 | 9F | IN7 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 160 | A0 | | | 0 - 65535 | unsigned int | |
| 161 | A1 | | | 0 - 65535 | unsigned int | |
| 162 | A2 | IN8 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 163 | A3 | | | 0 - 65535 | unsigned int | |
| 164 | A4 | | | 0 - 65535 | unsigned int | |
| 165 | A5 | IN9 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 166 | A6 | | | 0 - 65535 | unsigned int | |
| 167 | A7 | | | 0 - 65535 | unsigned int | |
| 168 | A8 | IN10 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 169 | A9 | | | 0 - 65535 | unsigned int | |
| 170 | AA | | | 0 - 65535 | unsigned int | |
| 171 | AB | IN11 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 172 | AC | | | 0 - 65535 | unsigned int | |
| 173 | AD | | | 0 - 65535 | unsigned int | |
| 174 | AE | IN12 T5 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 175 | AF | | | 0 - 65535 | unsigned int | |
| 176 | B0 | | | 0 - 65535 | unsigned int | |
| 177 | B1 | IN1 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 178 | B2 | | | 0 - 65535 | unsigned int | |
| 179 | B3 | | | 0 - 65535 | unsigned int | |
| 180 | B4 | IN2 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 181 | B5 | | | 0 - 65535 | unsigned int | |
| 182 | B6 | | | 0 - 65535 | unsigned int | |
| 183 | B7 | IN3 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 184 | B8 | | | 0 - 65535 | unsigned int | |
| 185 | B9 | | | 0 - 65535 | unsigned int | |
| 186 | BA | IN4 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 187 | BB | | | 0 - 65535 | unsigned int | |
| 188 | BC | | | 0 - 65535 | unsigned int | |
| 189 | BD | IN5 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 190 | BE | | | 0 - 65535 | unsigned int | |
| 191 | BF | | | 0 - 65535 | unsigned int | |
| 192 | C0 | IN6 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 193 | C1 | | | 0 - 65535 | unsigned int | |
| 194 | C2 | | | 0 - 65535 | unsigned int | |
| 195 | C3 | IN7 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 196 | C4 | | | 0 - 65535 | unsigned int | |
| 197 | C5 | | | 0 - 65535 | unsigned int | |
| 198 | C6 | IN8 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 199 | C7 | | | 0 - 65535 | unsigned int | |
| 200 | C8 | | | 0 - 65535 | unsigned int | |
| 201 | C9 | IN9 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 202 | CA | | | 0 - 65535 | unsigned int | |
| 203 | CB | | | 0 - 65535 | unsigned int | |
| 204 | CC | IN10 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 205 | CD | | | 0 - 65535 | unsigned int | |
| 206 | CE | | | 0 - 65535 | unsigned int | |
| 207 | CF | IN11 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 208 | D0 | | | 0 - 65535 | unsigned int | |
| 209 | D1 | | | 0 - 65535 | unsigned int | |
| 210 | D2 | IN12 T6 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 211 | D3 | | | 0 - 65535 | unsigned int | |
| 212 | D4 | | | 0 - 65535 | unsigned int | |
| 213 | D5 | IN1 T7 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 214 | D6 | | | 0 - 65535 | unsigned int | |
| 215 | D7 | | | 0 - 65535 | unsigned int | |
| 216 | D8 | IN2 T7 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 217 | D9 | | | 0 - 65535 | unsigned int | |
| 218 | DA | | | 0 - 65535 | unsigned int | |
| 219 | DB | IN3 T7 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 220 | DC | | | 0 - 65535 | unsigned int | |
| 221 | DD | | | 0 - 65535 | unsigned int | |
| 222 | DE | IN4 T7 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 223 | DF | | | 0 - 65535 | unsigned int | |
| 224 | E0 | | | 0 - 65535 | unsigned int | |
| 225 | E1 | IN5 T7 TARİFELİ SAYAÇ | R/W | 0 - 65535 | unsigned int | |
| 226 | E2 | | | 0 - 65535 | unsigned int | |
| 227 | E3 | | | 0 - 65535 | unsigned int | |

TARİFELİ SAYAÇ ENDEKSLERİ

| MODBUS REGISTER TABLOSU | | | | | | |
|---------------------------|---------|------------------------|------------------------|-----------|--------------|--------------|
| TARİFELİ SAYAÇ ENDEKSLERİ | ADDRESS | ADDRESS (HEX) | REGISTER | R/W | RANGE | FORMAT |
| | 228 | E4 | IN7 T8 TARİFELİ SAYAÇ | R/W | 0 – 65535 | unsigned int |
| | 229 | E5 | | | 0 – 65535 | unsigned int |
| | 230 | E6 | | | 0 – 65535 | unsigned int |
| | 231 | E7 | IN8 T8 TARİFELİ SAYAÇ | R/W | 0 – 65535 | unsigned int |
| | 232 | E8 | | | 0 – 65535 | unsigned int |
| | 233 | E9 | | | 0 – 65535 | unsigned int |
| | 234 | EA | IN10 T8 TARİFELİ SAYAÇ | R/W | 0 – 65535 | unsigned int |
| 235 | EB | 0 – 65535 | | | unsigned int | |
| 236 | EC | 0 – 65535 | | | unsigned int | |
| 237 | ED | IN11 T8 TARİFELİ SAYAÇ | R/W | 0 – 65535 | unsigned int | |
| 238 | EE | | | 0 – 65535 | unsigned int | |
| 239 | EF | | | 0 – 65535 | unsigned int | |

| CİHAZ DURUMU | ADDRESS | REGISTER | R/W | RANGE | FORMAT | |
|--------------|---------|----------|----------------------------|-------|--------------|--------------|
| | 240 | F0 | GÜN | R | 1 – 31 | unsigned int |
| | 241 | F1 | AY | R | 1 – 12 | unsigned int |
| | 242 | F2 | YIL | R | 0 – 99 | unsigned int |
| | 243 | F3 | SAAT | R | 0 – 23 | unsigned int |
| | 244 | F4 | DAKİKA | R | 0 – 59 | unsigned int |
| | 245 | F5 | SANIYE | R | 0 – 59 | unsigned int |
| | 246 | F6 | HAFTANIN GÜNÜ | R | 0 – 6 | unsigned int |
| | 247 | F7 | TARİFE | R | 0 – 8 | unsigned int |
| | 248 | F8 | SIRADAKİ YAZILACAK BLOK NO | R | 0 – 16383 | unsigned int |
| 249 | F9 | ALARM | R | 0 – 7 | unsigned int | |

| RS-485 A BİLGİLERİ | ADDRESS | REGISTER | R/W | RANGE | FORMAT | |
|-----------------------|---------|---------------|----------------------------|-----------|--------------|--------------|
| | 32768 | 8000 | BAUD RATE | R/W | 0 – 5 | unsigned int |
| | 32769 | 8001 | PARITY | R/W | 0 – 2 | unsigned int |
| | 32770 | 8002 | HABERLEŞME ADRESİ | R/W | 1 – 247 | unsigned int |
| | 32771 | 8003 | ŞİFRE | R/W | 0 – 9999 | unsigned int |
| | 32772 | 8004 | ŞİFRE ETKİNLEŞTİRME | R/W | 0 – 1 | unsigned int |
| | 32773 | 8005 | FLASH KAYIT SÜRESİ | R/W | 1 – 60 | unsigned int |
| | 32774 | 8006 | YAZ – KIŞ SAATI UYGULAMASI | R/W | 0 – 1 | unsigned int |
| | 32775 | 8007 | IN1 ÇARPAN | R/W | 0 – 65535 | unsigned int |
| | 32776 | 8008 | IN2 ÇARPAN | R/W | 0 – 65535 | unsigned int |
| 32777 | 8009 | IN3 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32778 | 800A | IN4 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32779 | 800B | IN5 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32780 | 800C | IN6 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32781 | 800D | IN7 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32782 | 800E | IN8 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32783 | 800F | IN9 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32784 | 8010 | IN10 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32785 | 8011 | IN11 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32786 | 8012 | IN12 ÇARPAN | R/W | 0 – 65535 | unsigned int | |
| 32787 | 8013 | IN1 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32788 | 8014 | IN2 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32789 | 8015 | IN3 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32790 | 8016 | IN4 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32791 | 8017 | IN5 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32792 | 8018 | IN6 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32793 | 8019 | IN7 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32794 | 801A | IN8 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32795 | 801B | IN9 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32796 | 801C | IN10 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32797 | 801D | IN11 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32798 | 801E | IN12 BÖLEN | R/W | 1 – 65535 | unsigned int | |
| 32799 | 801F | IN1 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32800 | 8020 | IN2 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32801 | 8021 | IN3 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32802 | 8022 | IN4 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32803 | 8023 | IN5 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32804 | 8024 | IN6 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32805 | 8025 | IN7 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32806 | 8026 | IN8 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32807 | 8027 | IN9 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32808 | 8028 | IN10 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32809 | 8029 | IN11 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32810 | 802A | IN12 BİRİM | R/W | 0 – 54 | unsigned int | |
| 32811 | 802B | GÜN | R/W | 1 – 31 | unsigned int | |
| 32812 | 802C | AY | R/W | 1 – 12 | unsigned int | |
| 32813 | 802D | YIL | R/W | 0 – 99 | unsigned int | |
| 32814 | 802E | SAAT | R/W | 0 – 23 | unsigned int | |
| 32815 | 802F | DAKİKA | R/W | 0 – 59 | unsigned int | |
| 32816 | 8030 | SANIYE | R/W | 0 – 59 | unsigned int | |
| 32817 | 8031 | HAFTANIN GÜNÜ | R | 0 – 6 | unsigned int | |

| MODBUS REGISTER TABLOSU | | | | | | |
|-------------------------|---------|------------------------|------------------------|-----------------|-----------------|--------------|
| TATİL TARİFESİ AYARLARI | ADDRESS | ADDRESS (HEX) | REGISTER | R/W | RANGE | FORMAT |
| | 32848 | 8050 | BAŞLANGIÇ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int |
| | 32849 | 8051 | BAŞLANGIÇ GÜNÜ / SAATI | R/W | 1 – 31 0 – 23 | unsigned int |
| | 32850 | 8052 | BİTİŞ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int |
| | 32851 | 8053 | BİTİŞ GÜNÜ / SAATI | R/W | 1 – 31 0 – 24 | unsigned int |
| | 32852 | 8054 | TARİFE | R/W | 0 – 8 | unsigned int |
| | 32853 | 8055 | BAŞLANGIÇ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int |
| | 32854 | 8056 | BAŞLANGIÇ GÜNÜ / SAATI | R/W | 1 – 31 0 – 23 | unsigned int |
| | 32855 | 8057 | BİTİŞ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int |
| | 32856 | 8058 | BİTİŞ GÜNÜ / SAATI | R/W | 1 – 31 0 – 24 | unsigned int |
| 32857 | 8059 | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32858 | 805A | BAŞLANGIÇ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32859 | 805B | BAŞLANGIÇ GÜNÜ / SAATI | R/W | 1 – 31 0 – 23 | unsigned int | |
| 32860 | 805C | BİTİŞ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32861 | 805D | BİTİŞ GÜNÜ / SAATI | R/W | 1 – 31 0 – 24 | unsigned int | |
| 32862 | 805E | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32863 | 805F | BAŞLANGIÇ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32864 | 8060 | BAŞLANGIÇ GÜNÜ / SAATI | R/W | 1 – 31 0 – 23 | unsigned int | |
| 32865 | 8061 | BİTİŞ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32866 | 8062 | BİTİŞ GÜNÜ / SAATI | R/W | 1 – 31 0 – 24 | unsigned int | |
| 32867 | 8063 | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32868 | 8064 | BAŞLANGIÇ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32869 | 8065 | BAŞLANGIÇ GÜNÜ / SAATI | R/W | 1 – 31 0 – 23 | unsigned int | |
| 32870 | 8066 | BİTİŞ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32871 | 8067 | BİTİŞ GÜNÜ / SAATI | R/W | 1 – 31 0 – 24 | unsigned int | |
| 32872 | 8068 | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32873 | 8069 | BAŞLANGIÇ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32874 | 806A | BAŞLANGIÇ GÜNÜ / SAATI | R/W | 1 – 31 0 – 23 | unsigned int | |
| 32875 | 806B | BİTİŞ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32876 | 806C | BİTİŞ GÜNÜ / SAATI | R/W | 1 – 31 0 – 24 | unsigned int | |
| 32877 | 806D | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32878 | 806E | BAŞLANGIÇ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32879 | 806F | BAŞLANGIÇ GÜNÜ / SAATI | R/W | 1 – 31 0 – 23 | unsigned int | |
| 32880 | 8070 | BİTİŞ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32881 | 8071 | BİTİŞ GÜNÜ / SAATI | R/W | 1 – 31 0 – 24 | unsigned int | |
| 32882 | 8072 | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32883 | 8073 | BAŞLANGIÇ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32884 | 8074 | BAŞLANGIÇ GÜNÜ / SAATI | R/W | 1 – 31 0 – 23 | unsigned int | |
| 32885 | 8075 | BİTİŞ YILI / AYI | R/W | 0 – 99 1 – 12 | unsigned int | |
| 32886 | 8076 | BİTİŞ GÜNÜ / SAATI | R/W | 1 – 31 0 – 24 | unsigned int | |
| 32887 | 8077 | TARİFE | R/W | 0 – 8 | unsigned int | |

| CUMARTESİ GÜNÜ TARİFE AYARLARI | ADDRESS | REGISTER | R/W | RANGE | FORMAT | |
|--------------------------------|---------|----------------------------|----------------------------|-----------------|-----------------|--------------|
| | 32888 | 8078 | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32889 | 8079 | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32890 | 807A | TARİFE | R/W | 0 – 8 | unsigned int |
| | 32891 | 807B | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32892 | 807C | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32893 | 807D | TARİFE | R/W | 0 – 8 | unsigned int |
| | 32894 | 807E | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32895 | 807F | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32896 | 8080 | TARİFE | R/W | 0 – 8 | unsigned int |
| 32897 | 8081 | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32898 | 8082 | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32899 | 8083 | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32900 | 8084 | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32901 | 8085 | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32902 | 8086 | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32903 | 8087 | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32904 | 8088 | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32905 | 8089 | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32906 | 808A | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32907 | 808B | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32908 | 808C | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32909 | 808D | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32910 | 808E | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32911 | 808F | TARİFE | R/W | 0 – 8 | unsigned int | |

BİRİM 0 - 54 :

| | | | | | | |
|--------------|-------------|----------------------|----------|----------|----------|-------------------|
| 0 = Birimsiz | 10 = CVArh | 20 = TEP | 30 = bbl | 40 = oz | 50 = nmi | ALARM 0 - 7 : |
| 1 = Wh | 11 = lmkWh | 21 = erg | 31 = gi | 41 = qtr | 51 = s | 0 = Alarm yok |
| 2 = VAh | 12 = ExkWh | 22 = L | 32 = pk | 42 = mm | 52 = min | 1 = Saat Hatası |
| 3 = VArh | 13 = lkvArh | 23 = m ³ | 33 = pt | 43 = cm | 53 = h | 2 = Tarih Hatası |
| 4 = kWh | 14 = CkvArh | 24 = m | 34 = qt | 44 = m | 54 = d | 3 = Tarih Hatası |
| 5 = kVAh | 15 = J | 25 = cl | 35 = g | 45 = km | | 4 = Tarife Hatası |
| 6 = kVArh | 16 = kJ | 26 = in ³ | 36 = kg | 46 = in | | 5 = Tarife Hatası |
| 7 = lmiWh | 17 = cal | 27 = ft ³ | 37 = t | 47 = ft | | 6 = Tarife Hatası |
| 8 = ExWh | 18 = kcal | 28 = yd ³ | 38 = GTN | 48 = yd | | 7 = Tarife Hatası |
| 9 = lVArh | 19 = BTU | 29 = gal | 39 = lb | 49 = mi | | |

| MODBUS REGISTER TABLOSU | | | | | | |
|----------------------------|---------|----------------------------|----------------------------|-----------------|-----------------|--------------|
| PAZAR GÜNÜ TARİFE AYARLARI | ADDRESS | ADDRESS (HEX) | REGISTER | R/W | RANGE | FORMAT |
| | 32912 | 8090 | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32913 | 8091 | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32914 | 8092 | TARİFE | R/W | 0 – 8 | unsigned int |
| | 32915 | 8093 | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32916 | 8094 | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32917 | 8095 | TARİFE | R/W | 0 – 8 | unsigned int |
| | 32918 | 8096 | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32919 | 8097 | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int |
| | 32920 | 8098 | TARİFE | R/W | 0 – 8 | unsigned int |
| 32921 | 8099 | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32922 | 809A | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32923 | 809B | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32924 | 809C | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32925 | 809D | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32926 | 809E | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32927 | 809F | BAŞLANGIÇ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32928 | 80A0 | BİTİŞ SAATI / DAKİKASI | R/W | 0 – 24 0 – 59 | unsigned int | |
| 32929 | 80A1 | TARİFE | R/W | 0 – 8 | unsigned int | |
| 32930 | | | | | | |